

INSTRUCTIONS FOR DOWNLOADING "FFC" FILES TO RADIO SHACK SCANNERS

SPECIAL NOTE: THESE INSTRUCTIONS ARE FOR RADIO SHACK SCANNER MODELS PRO 83, PRO 84, PRO 79 & PRO 89 ONLY! THERE ARE OTHER MODELS OF RADIO SHACK SCANNERS THAT CAN USE THESE DOWNLOADS BUT DATA MUST BE REARRANGED BY CUTTING AND PASTING -C & P FUNCTIONS ARE IN THE PROGRAM. THIS IS NECESSARY TO MATCH THE NUMBER OF FREQUENCIES IN EACH BANK TO THE SPECIFIC SCANNERS 50 OR 100 CHANNEL BANKS AND THE SCANNERS NUMBERING SYSTEM (SOME BANKS START WITH #0 WHILE OTHERS BEGIN WITH #1). SEE A LIST OF OTHER RADIO SHACK SCANNERS SUPPORTED BY THE "SCANCAT-LITE PLUS". SEE DETAILS AND PURCHASE ONLINE AT www.scancat.com

NOTE: The editors of SCANCAT-LITE PLUS! refer to the RS scanner as "radio" throughout their program.

OPEN "SCANCAT-LITE PLUS!" PROGRAM.

Note: ALL "CLICKS" IN THESE INSTRUCTIONS ARE LEFT MOUSE CLICKS!

Click on "PROGRAM RADIO" - *(it takes a few moments for the screen to open)*

Click on "SELECT RADIO"

Click on "ACCEPT"

Click on "Files"

Click on "Load File"

Click on "PERSONAL DATABASE FILES (RSD)"

AT THIS POINT ANOTHER SCREEN WILL APPEAR IN THE UPPER LEFT QUARTER OF THE DISPLAY SCREEN.

Determine which racing series you desire to download into the scanner (xxxxx.rsd) and Click it. Then click "Open"

Click "Load Radio" (top gray line on screen)

Then select and click "Load Freqs ALL Banks at once F8"

At this point a small "Pop Up Screen" will appear in the center of the computer screen with instructions:

Turn your scanner on at this time!

Plug the RS correct computer to scanner programming cable into the scanner.

Scanner will go into "WIRED" Mode automatically.

While the scanner says "WIRED" press and HOLD the "4" key (on the scanner) down for a few seconds so it can change the Baud rate to 9600 (appears nothing is happening but it is).

Then click "OK" to continue.

Scanner counts up through Loading 1-200 as screen goes through loading each channel (white box with red outline) jumps over each channel as it is loaded!

Scanner screen will read "END" when finished. Computer screen goes back to Channel 1 Bank 1 when finished.

TURN SCANNER "OFF"

UNPLUG PROGRAMMING CABLE FROM SCANNER

YOUR SCANNER IS LOADED

TO CLOSE THE SCANCAT-LITE PLUS PROGRAM, CLICK ON "DATA BASE VIEW" THEN CLICK "CLOSE TOP DATABASE" THEN CLICK "EXIT" TO CLOSE THE PROGRAM.